



INVESTOR IN PEOPLE


The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed 

Dated 4 November 2004

BEST AVAILABLE COPY

The Patent Office

Cardiff Road
Newport
South Wales
NP9 1RH

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

THE PATENT OFFICE

28 OCT 2003

NEWPORT

1. Your reference

JM/P206985

2. Patent application number

(The Patent Office will fill in this part)

0325095.8

28 OCT 2003

3. Full name, address and postcode of the or of each applicant (underline all surnames)

Filtronic Plc
The Waterfront
Salts Mill Road, Saltaire
Shipley, BD18 3TT

Patents ADP number (if you know it)

If the applicant is a corporate body, give the country/state of its incorporation

United Kingdom

4. Title of the invention

A COPLANAR WAVEGUIDE LINE

5. Name of your agent (if you have one)

URQUHART-DYKES & LORD LLP

"Address for service" in the United Kingdom to which all correspondence should be sent (including the postcode)

Tower North Central
Merrion Way
Leeds, LS2 8PA
United Kingdom

Patents ADP number (if you know it)

1644004

08857138001

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number

Country

Priority application number
(if you know it)

Date of filing
(day / month / year)

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Date of filing
(day / month / year)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if:

YES

a) any applicant named in part 3 is not an inventor, or

b) there is an inventor who is not named as an applicant, or

c) any named applicant is a corporate body.

See note (d))

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document-

Continuation sheets of this form

Description	11
Claim(s)	3
Abstract	1
Drawing(s)	13 + 13

10. If you are also filing any of the following, state how many against each item.

Priority documents	-
Translations of priority documents	-
Statement of inventorship and right to grant of a patent (Patents Form 7/77)	-
Request for preliminary examination and search (Patents Form 9/77)	-
Request for substantive examination (Patents Form 10/77)	-
Any other documents (please specify)	-

11.

I/We request the grant of a patent on the basis of this application.

Signature

Date

27/10/03

12. Name and daytime telephone number of person to contact in the United Kingdom

Mr Johnathan McDonough - 0113 245 2388

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.*
- Write your answers in capital letters using black ink or you may type them.*
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.*
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.*
- Once you have filled in the form you must remember to sign and date it.*
- For details of the fee and ways to pay please contact the Patent Office.*

A COPLANAR WAVEGUIDE LINE

The present invention relates to a coplanar waveguide line.
The present invention also relates to a Mach-Zehnder modulator
5 including such a coplanar waveguide line.

The use of Mach-Zehnder modulators as attenuators of optical
signals is well known. IEEE Transactions on Microwave Theory
and Techniques, Volume 47, No. 7, July 1999 provides a
10 background review of the operation of such devices.

The bandwidth of such a modulator is inversely proportional to
the mismatch in propagation speed between lightwaves and
microwaves through the device. Typically, when using
15 substrates such as gallium arsenide one tries to slow the
speed of the microwaves to match the speed of the lightwaves
to broaden the bandwidth of the device. With a lithium niobate
substrate one does the reverse.

Known coplanar waveguide lines comprise a central electrode
strip and first and second electrode strips, one on each side
to the central electrode strip. In use the first and second
electrode strips have the same polarity which is opposite to
that of the central electrode strip. T-rails extend from both
20 sides of the central strip into proximity with first and
25 second optical waveguides to provide the slow wave effect.

Such coplanar waveguides are generally used with un-doped
epitaxial layers. This has the advantage of very low
30 microwave loss. However, the driving voltage must be high due
to the poor overlap between the lightwaves and microwaves.

Asymmetric coplanar strip lines are also used as slow wave
structures. Asymmetric coplanar strips lack a central
35 electrode strip. The optical waveguides are disposed between

first and second parallel electrode strips which in use have opposite polarities. T-rails extend from the strips to the waveguides.

5 Unlike with coplanar waveguide lines, asymmetric coplanar strips are used on substrates including an n^+ electrically conducting layer extending between the waveguides. Use of a conducting layer reduces the driving voltage but increases the microwave loss.

10 It is known in the art not to include n^+ conducting layers in the epitaxial layers of coplanar waveguides. Whilst this improves the overlap between the lightwaves and microwaves (so reducing driving voltage) this results in excessive
15 capacitance making true push/pull operation impossible.

Accordingly, in a first aspect, the present invention provides a coplanar waveguide line comprising

20 a substrate;
a central electrode strip on the substrate;
first and second electrode strips disposed on opposite sides of the central electrode strip and extending parallel thereto;
first and second optical waveguides on the substrate, the
25 optical waveguides being positioned between the first and central electrode strips and extending parallel thereto;
the central electrode comprising at least one T-rail extending proximate to the first optical waveguide;
the first electrode comprising at least one T-rail
30 extending proximate to the second optical waveguide;
the substrate comprising an n^+ electrically conducting layer extending between the optical waveguides;
wherein the coplanar waveguide line further comprises an
35 electrical connection between first and second electrode strips.

The coplanar waveguide according to the invention has the advantage that it combines the low microwave loss of known coplanar waveguides with the lower driving voltage of asymmetric coplanar strips in combination with the conducting n^+ layer. In addition, since T-rails are only added on one side of the central electrode, capacitance can be halved giving greater freedom for transmission line design and making the transmission line applicable for MMIC transmission line design.

In addition it is known that there is discontinuity at the transmission between coplanar waveguides and asymmetric coplanar strips or vice versa. This can often restrict the choice of whether a coplanar waveguide or asymmetric coplanar strip should be used during design of a device. No such discontinuities exist between the coplanar waveguide line of the invention and known waveguide structures.

Preferably, the electrical connection between first and second electrode strips is an airbridge. The electrical connection can be wire bonded between the first and second electrode strips. The electrical connection between the first and second electrodes can extend through the back of the substrate. Such means of connection provide reliable and relatively straightforward means of connecting the first and second electrode strips.

Preferably, the coplanar waveguide line comprises a plurality of electrical connections between first and second electrode strips, the electrical connections preferably being equally spaced. Such multiple connections minimise the effects of unbalanced loading of the capacitance of the coplanar waveguide.

Preferably, at least one of the central electrode strip and first electrode strip comprise a plurality of T-rails, preferably equally spaced.

5 The T-rail can comprise a contact pad connected to the corresponding electrode strip by a bridge. Preferably, the contact pad abuts the optical waveguide. This ensures good overlap between lightwaves and microwaves.

10 The substrate can comprise a first isolation trench which extends through the n^+ electrically conducting layer between the first electrode strip and optical waveguides. The substrate can comprise a second isolation trench extending through the n^+ electrically conducting layer between the
15 central electrode strip and the optical waveguides. The substrate can comprise a third isolation trench extending through the n^+ electrically conducting layer between the central electrode strip and the second electrode strip.

20 In a further aspect of the invention there is provided a Mach-Zehnder modulator including a coplanar waveguide according to the invention.

The present invention will now be described by way of example
25 only, and not in any limitative sense with reference to the accompanying drawings in which

figures 1a and 1b show a schematic view of a Mach-Zehnder modulator;

30

figure 2 shows a further schematic view of a Mach-Zehnder modulator and accompanying electrode strips;

35

figure 3 shows a known asymmetric coplanar strip in perspective view;

figure 4 shows the asymmetric coplanar strip of figure 3 in cross section;

5 figure 5 shows the asymmetric coplanar strip of figures 3 and 4 in plan view;

figure 6 shows a known coplanar waveguide strip in cross section;

10 figure 7 shows the coplanar waveguide strip of figure 6 in plan view;

figure 8 shows a first embodiment of a coplanar waveguide line according to the invention in cross section;

figure 9 shows a second embodiment of a coplanar waveguide line according to the invention in cross section;

20 figure 10 shows the coplanar waveguide line of figure 9 in plan view.

figure 11 shows a further embodiment of a coplanar waveguide line according to the invention; and

25 figures 12 and 13 show performance data for the coplanar waveguide line according to the invention.

Shown in figure 1 in schematic form is a Mach-Zehnder modulator (1). The Mach-Zehnder modulator (1) comprises input and output optical waveguides (2,3) and two optical paths (4,5) extending therebetween. The two optical paths (4,5) are of substantially equal length.

In use, a coherent light beam is inserted into the Mach-Zehnder modulator (1). The beam is split into approximately equal halves which travel down the two separate paths (4,5) to the output waveguide (3). The light beams re-combine in the output waveguide (3) before exiting the device. Assuming the two paths are of equal length then when the two beams re-combine they are in phase and the resulting output beam is of the same intensity as the input beam.

If one introduces a phase shift into one of the arms (4,5) of the Mach-Zehnder modulator (1) (as shown in figure 1b) then when the two beams re-combine they are slightly out of phase. This results in a reduction in the intensity of the output beam as shown.

A common method of introducing a phase shift into the arms (4,5) of a Mach-Zehnder modulator is shown in schematic form in figure 2. In close proximity to each of the arms (4,5) of the Mach-Zehnder modulator (1) is a conducting electrode strip (6,7). A microwave generator (8) is connected to the electrode strips (6,7) and the resulting electromagnetic fields generated interact with light passing through the arms (4,5) so altering the phase of the light. As shown, it is usual to connect the electrode strips (6,7) in a push/pull configuration such that the voltage applied to the two electrode strips (6,7) is 180 degrees out of phase. This maximises the phase changing effect of the electro magnetic waves.

The bandwidth of the Mach-Zehnder modulator (1) is limited by the mismatch of the propagation speed between the microwaves along the electrode strips (6,7) and lightwaves along the arms (4,5) of the Mach-Zehnder modulator (1). The bandwidth is
5 given by the formula

$$\Delta f_{3dB/TT} = \frac{1.4c_{ph}}{\pi(n_{opt} - n_{mw})L_T}$$

10

For GaAs, $n_{opt} \approx 2.64$, $n_{mw} \approx 3.34$ and $L_T = 0.01$ meter, resulting in a 3dB bandwidth of $\approx 19\text{GHz}$

15 In order to overcome this problem and to broaden the bandwidth of the Mach-Zehnder modulator (1) one typically attempts to reduce the speed of propagation of the microwaves through the device. There are essentially two forms of known slow
..... waveguide structure - the coplanar waveguide line (9) and the
20 asymmetric coplanar strip line (10).

Shown in figure 3 in perspective view is an known asymmetric coplanar strip (ACPS) (10). The ACPS (10) comprises a substrate (11) having positioned thereon first and second
25 strip electrodes (12,13). Positioned between the strip electrodes (12,13) and extending parallel thereto are first and second optical waveguides (14,15). T-rails (16) extend from the strip electrodes (12,13) into proximity with the optical waveguides (14,15). Each T-rail (16) comprises a
30 contact pad (17) which abuts the optical waveguide (14,15) and an airbridge (18) extending between contact pad (17) and corresponding strip electrode (12,13).

Positioned within the substrate (11) is an n^+ conducting layer
35 (19). As can be seen in figure 4, the n^+ conducting layer (19)

extends between the optical waveguides (14,15) providing an electrical connection therebetween. Isolation trenches (20,21) extend through the n^+ conducting layer (19) at the sides of the optical waveguides as shown. The n^+ conducting layer (19) extends beneath the electrode strips (12,13).

Figure 5 shows the asymmetric coplanar strip (10) of figures 3 and 4 in plan view. Both electrode strips (12,13) comprise a plurality of T-rails (16) extending to the associated optical waveguide (14,15). The T-rails (16) are equally spaced. The T-rails (16) slow the microwaves, increasing bandwidth.

Due to the presence of the n^+ conducting layer (19) asymmetric coplanar strips (10) only require a low driving voltage. However, they tend to have poor microwave loss characteristics.

Shown in figure 6 in cross section is a known coplanar waveguide line (9). The coplanar waveguide line (9) comprises a GaAs substrate (11). Positioned on the substrate (11) is a central electrode strip (22) having first and second electrode strips (12,13) arranged on the opposite side thereof. First and second optical waveguides (14,15) are positioned between the first (12) and central (22) and central (22) and second (13) electrode strips respectively. T-rails (16) extend from both sides of the central electrode strip (22) and also both first and second electrode strips (12,13). T-rails (16) from the second electrode strip (13) and the central electrode strip (22) abut the optical waveguides (14,15) as shown. The GaAs substrate (11) does not include an n^+ conducting layer.

Due to the absence of a n^+ conducting layer, a coplanar waveguide line (9) has a very low microwave loss. However, the driving voltages must be quite high due to the bad overlap between lightwaves and microwaves.

The coplanar waveguide line (9) is shown in plan view in figure 7 showing the repeating nature of the T-rails (16).

Shown in figure 8 is a coplanar waveguide line (9) according to the invention in cross section. The coplanar waveguide line (9) comprises a GaAs substrate (11) having an n⁺ conducting layer (19) embedded therein. Positioned on the substrate (11) are a central electrode strip (22) and first and second electrode strips (12,13) one on each side of the central electrode strip (22) and extending parallel thereto. Two parallel optical waveguides (14,15) are positioned between the first electrode strip (12) and central electrode strip (22) and extend parallel thereto. T-rails (16) extend from the first (12) and central (22) electrode strips to the optical waveguides (14,15) as shown. A conducting n⁺ layer (19) extends underneath the two optical waveguides (14,15). First and second isolation trenches (20,21) extend through the n⁺ layer (19) on each side of the optical waveguides (14,15) as shown. The first and second electrode strips (12,13) are electrically connected together by wire bonding (23). In a further embodiment (not shown) the first and second electrode strips (12,13) are connected by airbridges.

A further embodiment of a coplanar waveguide line (9) according to the invention is shown in figure 9. The coplanar waveguide line (9) in this embodiment is similar to that of the previous embodiment except the n⁺ conducting layer (19) extends from underneath the central electrode strip (22) to the second electrode strip (13) as shown. As with the previous embodiment however this extension of the n⁺ conducting layer (19) is separated from the n⁺ layer (19) under the optical waveguides (14,15) by the second isolation trench (21). A third isolation trench (24) extends through the n⁺ conducting layer (19) between the second (13) and central (22) strip electrodes.

(

Shown in figure 10 is the coplanar waveguide line (9) of figure 9 in plan view. This figure shows the repeating nature of the T-rails (16) along the electrode strips (12,22). The first and second electrode strips (12,13) are electrically connected by a plurality of air bridges (25), the air bridges (25) are substantially equally spaced. In an alternative embodiment the first and second electrode strips (12,13) are electrically connected by wire bonding (23).

Shown in figure 11 is a further embodiment of a coplanar waveguide line (9) according to the invention in cross section. This embodiment is similar to that shown in figure 8 except the first and second electrode strips (12,13) are connected by electrical connections (26) which extend through the substrate.

Shown in figures 12 and 13 are data relating to the performance of the coplanar waveguide line according to the invention.

The magnitude of S21 and S11 of the measured S-parameters on a coplanar waveguide line are shown in figure 12 and 13 respectively. In figure 12 and figure 13, the large difference between two plots is attributed to presence of absence of ground strapping. In figure 13, strong resonances appear regularly in S11 spectrum for a CPW without ground strapping when the frequency is increased. These resonances correspond to the ripples in the S21 spectrum for the CPW shown in figure 12. The resonances disappeared after the strapping between the first and second electrode strips have been done. Smooth responses up to 30 Ghz on S21 and low reflection on S11 have been realised with the use of ground strapping.

The electrical contacts extending between first and second strip electrodes (12,13) eliminate any unbalanced performance of the coplanar waveguide line due to asymmetric capacitive loading of the central electrode strip (22).

5

The coplanar waveguide line (9) of the invention has a number of advantages over known coplanar waveguide lines and asymmetric coplanar strips. Since only one side of the central electrode strip (22) is capacitively loaded with T-rails (16) this gives a greater choice of transmission line design and makes the line applicable for MMIC transmission line design. In addition, the coplanar waveguide line (9) has low microwave loss coupled with the advantage of low driving voltage and high speed. There is also no restriction as to when choices should be made between coplanar waveguide and asymmetric coplanar strips on doped or un-doped epitaxial layers.

CLAIMS

1. A coplanar waveguide line comprising

a substrate;

a central electrode strip on the substrate;

first and second electrode strips disposed on opposite sides of the central electrode strip and extending parallel thereto;

first and second optical waveguides on the substrate, the optical waveguides being positioned between the first and central electrode strips and extending parallel thereto;

the central electrode comprising at least one T-rail extending proximate to the first optical waveguide;

the first electrode comprising at least one T-rail extending proximate to the second optical waveguide;

the substrate comprising an n^+ electrically conducting layer extending between the optical waveguides;

wherein the coplanar waveguide line further comprises an electrical connection between first and second electrode strips.

2. A coplanar waveguide line as claimed in claim 1, wherein the electrical connection between first and second electrode strips is an airbridge.

3. A coplanar waveguide line as claimed in claim 1, wherein the electrical connection is wire bonded between the first and second electrode strips.
- 5 4. A coplanar waveguide line as claimed in claim 1, wherein the electrical connection between first and second electrodes extends through the back of the substrate.
- 10 5. A coplanar waveguide line as claimed in any one of claims 1 to 4, comprising a plurality of electrical connections between first and second electrode strips, the electrical connections preferably being equally spaced.
- 15 6. A coplanar waveguide line as claimed in any one of claims 1 to 5, wherein at least one of the central electrode strip and first electrode strip comprises a plurality of T-rails, preferably equally spaced.
- 20 7. A coplanar waveguide line as claimed in any one of claims 1 to 6, wherein the T-rail comprises a contact pad electrically connected to the corresponding electrode strip by an airbridge.
- 25 8. A coplanar waveguide line as claimed in claim 7, wherein the contact pad abuts the optical waveguide.
- 30 9. A coplanar waveguide line as claimed in any one of claims 1 to 8, wherein the substrate comprises a first isolation trench which extends through the n^+ electrically conducting layer between the first electrode strip and optical waveguides.
- 35 10. A coplanar waveguide line as claimed in any one of claims 1 to 9, wherein the substrate comprises a second isolation trench extending through the n^+ electrically

conducting layer between the central electrode strip and the optical waveguides.

- 5 11. A coplanar waveguide line as claimed in any one of claims 1 to 10, wherein the substrate comprises a third isolation trench extending through the n^+ electrically conducting layer between the central electrode strip and the second electrode strip.
- 10 12. A Mach-Zehnder modulator including a coplanar waveguide line as claimed in any one of claims 1 to 11.
13. A coplanar waveguide line substantially as hereinbefore described.
- 15 14. A coplanar waveguide line substantially as hereinbefore described with reference to the drawings.
- 20 15. A Mach-Zehnder modulator substantially as hereinbefore described.
16. A Mach-Zehnder modulator substantially as hereinbefore described with reference to the drawings.

25

Abstract

A coplanar waveguide line comprising

5

a substrate;

a central electrode strip on the substrate;

10

first and second electrode strips disposed on opposite
sides of the central electrode strip and extending
parallel thereto;

15

first and second optical waveguides on the substrate, the
optical waveguides being positioned between the first and
central electrode strips and extending parallel thereto;

the central electrode comprising at least one T-rail
extending proximate to the first optical waveguide;


20

the first electrode comprising at least one T-rail
extending proximate to the second optical waveguide;


25

the substrate comprising an n^+ electrically conducting
layer extending between the optical waveguides;

wherein the coplanar waveguide line further comprises an
electrical connection between first and second electrode
strips.





() The Y Branch could be replaced by any other kinds of 3 dB couplers, such as X junction, DC, MMJs




~ Lightwave


~ Microwave











9
















S-parameters of a CPW with and without ground strapping



S parameters of a CPW with and without ground strapping



Document made available under the Patent Cooperation Treaty (PCT)

International application number: PCT/GB04/004515

International filing date: 27 October 2004 (27.10.2004)

Document type: Certified copy of priority document

Document details: Country/Office: GB
Number: 0325095.8
Filing date: 28 October 2003 (28.10.2003)

Date of receipt at the International Bureau: 19 November 2004 (19.11.2004)

Remark: Priority document submitted or transmitted to the International Bureau in compliance with Rule 17.1(a) or (b)



World Intellectual Property Organization (WIPO) - Geneva, Switzerland
Organisation Mondiale de la Propriété Intellectuelle (OMPI) - Genève, Suisse

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record.**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☒ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER: _____**

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.